

STRATA CIX SYSTEM: PHONE & VOICEMAIL USER GUIDE



One Call | infinite solutions

Business Communications Solutions
9910 Irvine Center Drive
Irvine, CA 92618

www.bcscsconsultants.com

[m] 949.333.1000

[f] 949.333.1001

Everything Your Business Needs





GETTING TO KNOW YOUR PHONE

**** Some features may already be pre-programmed ****



20 Programmable Feature Buttons 4-Line LCD Telephone






Legend

- | | |
|-------------------------------------|-----------------------|
| A. Status LED (message and ringing) | G. Speaker LED Button |
| B. LCD Display | H. Volume |
| C. Softkeys | I. Hold Button |
| D. Programmable Feature Buttons | J. Microphone |
| E. Message Waiting LED Button | K. Tilt stand |
| F. Microphone LED Button | |

Everything Your Business Needs





Button	Definitions
	<p>Message (Msg): When Msg LED flashes, press Msg to call back the station or voice mail device that activated the LED. This is the telephone's [PDN] message waiting button.</p> <p>Important! <i>Red LED must be on in order for button to function.</i></p>
	<p>Microphone (Mic/Mute) button toggles between Mic and Mute. When Mic key is lit, Mute is disabled. When Mic is pressed again and light is off, Mute is enabled on the microphone in the telephone and the microphone in the handset.</p>
	<p>Speaker: Press to toggle the speaker ON/OFF. When red Speaker LED is lit handsfree communications is supported.</p> <p>To start a handsfree conversation; press the Speaker button, this turns the red Speaker LED on. To terminate this call press the Speaker button again (Speaker LED off).</p> <p>During a handset conversation, press the Speaker button to start hands-free communications (red Speaker LED on). Press the Speaker button again to transfer the conversation back to the handset (Speaker LED off).</p>
	<p>Press and release the volume control bar to adjust volume levels. See "Volume Control" on page 13.</p> <p>Important! <i>Continuously holding the volume button (up or down) does not change the volume. It is adjusted on a per press basis.</i></p>
	<p>Navigation Key: Round button on the IP513 telephone is a navigation key used for moving the cursor on html pages and in the programming screens. Center of the button is the "select" function. The arrows are used to scroll up, down, left or right.</p>

Description	Image
<p>Digital Single Line Telephone:</p> <ul style="list-style-type: none"> • On hook dialing • Headset I/F • Ringing LED • Non-display 	
<p>10 Button Digital Telephone:</p> <ul style="list-style-type: none"> • Half duplex Speakerphone • Headset I/F • Ringing LED • Non-display 	
<p>10 Button Digital Telephone:</p> <ul style="list-style-type: none"> • 4 line LCD with back light option • Half duplex Speakerphone • Headset I/F • Ringing LED 	

Everything Your Business Needs



Voice



Network



Cabling



VOIP




Security



PM



Internet

Description	Image
<p>20 Button Digital Telephone:</p> <ul style="list-style-type: none"> • 4 line LCD with back light option • Half duplex Speakerphone • Headset I/F • Ringing LED 	
<p>10 Button with Electronic LCD Labels:</p> <ul style="list-style-type: none"> • 9 line LCD with back light • Half duplex and Full duplex Speakerphone options • Headset I/F • Ringing LED 	

PHONE USER GUIDE

• PLACE A CALL

From the Handset: Lift the handset, then dial the number (you can switch to speakerphone by pressing **Spkr** and hanging up handset). *

From the Speaker: Press **Spkr.**, then dial the # (you can switch to handset by lifting handset). *

* For Outside Line: Dial "9" then "1 + Area Code" & Phone #.

• DIAL OUT OF THE DIRECTORY

1. Press **DIR** soft key.
2. Choose directory you wish to access and use dial pad to enter name:

Everything Your Business Needs





My = Personal Speed Dial, **EXTR**=System Speed dial Names, **INTR**= Internal Extensions, **Dial** = Cancels directory.

- Press **FIND** to start directory search.
- Press **NEXT** to move forward.
- Press **BACK** to move backwards.
- Press **CALL** to connect to the directory entry selected.
- Press **CNCL** to quit the directory search.

• ANSWERING A CALL

Lift the handset or press **Spkr**.

• HOLD A CALL

Hold: To place a call on hold, Press the Hold button. To return to the held call, press the held line's button.

Exclusive Hold: To place a call on Exclusive hold, press hold twice.

• PARK A CALL

1. While on a call, press **Call Park**.
2. Specify the Park Orbit using one of the following:
 - Enter a valid extension.
 - Press **#** and the system automatically selects your extension as the orbit.
 - Press ***** and the system automatically selects a General Park Orbit between **7000-7019**. The chosen orbit appears on the LCD.
3. Hang up. If the parked call is not retrieved, the call rings back to your phone.
4. To Pick up a parked call:
 - From any phone: press **Call Park** and the extension number or orbit # it is parked at.
 - If somebody has parked the call on your extension, simply press the **Call Park** button to pick up the call.

• TRANSFER A CALL

1. **Blind Transfer** (transfer directly) - Press **Cnf/Trn** and dial the extension number you would like to transfer it to. When you hear the phone ringing you can hang up.
2. **Supervised Transfer** (Announce a call before transferring) – While on a call, press **Cnf/Trn** and dial the extension number, wait for the other party to answer the phone. If they would like to

Everything Your Business Needs





take the call you can hang up and it will get transferred. If they don't and you'd like to reconnect to the original caller, press your extension button which should be flashing.

3. **Transferring a Call Directly to Voice Mail** (If you have a programmed VM Transfer Key)

After you have answered the incoming call:

- Press the Transfer to Voice Mail Key (The call will be placed on hold automatically)
- Enter the destination Mail Box Number
- Press the # Key to transfer the call

4. **Transferring a Call Directly to Voice Mail** (If you do NOT have a VM Transfer programmed key)

- Dial #, 4, 0, 7 (The call will be placed on hold automatically)
- Enter the destination Mail Box Number
- Press the # Key to transfer the call

● **CONFERENCE CALL**

1. While on a call, Press **Cnf/Trn**.
2. Call another station or outside line.
3. When the called party answers, press the **Cnf/Trn** button. (If you receive a busy tone or if the station does not answer, press the flashing line button to return to the original call).
4. Repeat Steps 1-3 to add more lines. You can conference up to 8 parties.

To Transfer Conference Control: When the person who initiates the conference (master) hangs up, control transfers to the 1st internal station added to the conference. If no internal stations are in the conference, the call disconnects.

1. Perform Steps 1 & 2 above to add the line to which you wish to transfer conference control.
2. Announce the call and hangup to transfer the call. This station is now the conference "master" with the ability to add/delete parties.

To Hold a Conference Call: If you are the "master" conference controller, press **Hold** once (or twice for Executive Hold) to place the conference call on hold. The conference continues and you can join at any time without giving up "master" abilities. Music-on-hold is suppressed in this mode.

To Hold 2 Outside Lines:

1. While talking on an outside call, press **Cnf/Trn**.
2. Access an outside line.

Everything Your Business Needs





3. After the party answers, press **Cnf/Trn** twice and hang up. If you receive a busy tone or if station doesn't answer, press the flashing line button to return to original call.

- **CALL FORWARDING (internal & external)**

Enter the button sequence below:

All Calls: Press Ext. + **#6011** + Destination Number + #

Busy: Press Ext. + **#6021** + Destination Number + #

No Answer: Press Ext. + **#6031** + Destination # + Timer (seconds, 2-digits) + #.

Busy No Answer: Press Ext. + **#6041** + Destination # + Timer (seconds, 2-digits) + #.

Cancel: Press Ext. + **#6051**.

- **VOLUME CONTROL**

1. To adjust handset volume during a call: press down **Vol ▲** or **Vol ▼**.
2. To adjust speaker volume for internal/external calls and background music: Press **Spkr** and use **Vol ▲** or **Vol ▼** to adjust volume level. Press **Spkr** to exit.
3. To adjust Ring Tone, Handsfree Answerback and Speaker Off-hook Call Announce: With an idle phone and handset on-hook, press **Vol ▲** or **Vol ▼**.

- **SPEED DIAL**

To Store a Station Speed Dial Number:

1. Dial **#9876**.
2. Press **Spdial**.
3. Enter a Speed Dial Code (**100-199**).
4. Enter the number to be stored (32 digits max).
5. Press **Spdial** button to store the entry.
6. Repeat steps 2-5 to add more speed dial numbers.
7. To end programming session, lift and replace the handset.

To Clear a number from a Station Speed Dial code:

Repeat the previous procedure skipping Step 4

To Make a call using Speed Dial:

1. Lift the handset. Press **Spdial**, then dial the Speed Dial Number.
2. Access an outside line (if necessary).

Everything Your Business Needs





* Note: You may need to lift the handset and access an outside line before pressing **Spdial** (depending on your telephone setup)

● **PAGING**

To make a Page Announcement to telephones or external speakers

1. Lift the handset, press your extension button and enter **#30**
2. Make your announcement, then hang up.

VOICEMAIL USER GUIDE

➤ **To check Voicemail from outside: Call direct line. Hit * after greeting starts and follow prompts**

TOSHIBA

**Strata
CIX**

*Strategy ES
Voice Processing System*

Quick Reference Guide

Access Strategy ES

Call Strategy ES at _____.

Press ***** and enter your Mailbox number.

Enter your security code. (If you make a mistake while entering the code, press ***** to re-enter.)

Strategy ES plays the number of messages you have and prompts you with Main Menu choices.

MAIN MENU

- 1** Play Messages
- 2** Send Messages
- 3** Manage Mailbox
- 4** Retrieve/Listen to E-mail Messages[†]
- 0** Exit user mode
- #** Hang up

[†]Plays only if TTS and UM is available

1 PLAY MESSAGES

- 1** Play the next message
- * 1** Replay the current message
- 2** Save the current message
 - 1** Standard Save Message Folder
 - 2 ~ 8** Personal Message Folder(s)
- * 2** Play the **Previous** message
- 3** Delete the current message
- 5** Forward the current message
- 6** Reply to the current message
- 7** Special Functions
 - 0** Immediate Fax print of all fax documents within a folder^{††}
 - 1** Immediate Fax print of current fax document^{††}
 - 2** Send All Fax documents within a folder to fax machine for print^{††}
 - 3** Send Current Fax to fax machine for print^{††}
 - 4** Message Date and Time
 - 5** Future Delivery Review
 - 6** Continuous Delete
 - 7** Access New/Saved message folders (toggle)
 - 8** Continuous Play
 - 9** Return to previous menu
- 9** Return to Main Menu

^{††}Optional feature

Everything Your Business Needs





2 SEND MESSAGES

Enter **destination** (one of the following):

Mailbox Number plus **#**

- 0 0** Directory plus name
- 0 1** Personal Distribution List (1~25)
- 0 4** Multiple Destinations

Record

Record a message, comment or reply
(Press **#** when finished.)

- #** Send and Return to Main Menu
- 1** Review recording
- 2** Re-record
- 3** Append recording
- 4** Select Additional Destinations
- 7** Special Delivery Options
 - 1** Set Urgent status (On/Off)
 - 2** Set Private status (On/Off)
 - 3** Set Return Receipt request (On/Off)
 - 9** Return to previous menu
- 8** Set Future Delivery
- * *** Cancel message and select new destination
- * *** Cancel and Return to Main Menu

3 MANAGE MAILBOX

- 1** Change Greeting
- 2** Change User Options
 - 1** Change Do Not Disturb (On/Off)
 - 2** Change Call Screening (On/Off)
 - 3** Change Security Code
 - 4** Select Busy Greeting (On/Off)
 - 5** Record Busy Greeting
 - 6** Record your Name
 - 7** Change message Notification
 - 8** Set up Automatic Message Copy
 - * *** Review Option Settings
 - 9** Return to previous menu
- 3** Manage Personal Distribution Lists
- 4** Manage Guest Mailboxes
- 5** Manage Personal Message Folders
- 9** Return to Main Menu

• New Message Light

If you have checked all your new messages, but the New Message Light on your phone is still flashing:

1. Dial #, 4, 0, 9
2. Press the Soft Key under the display labeled as RLS

This should turn the New Message Light Off

Everything Your Business Needs





BCS INFORMATION

CONTACT INFORMATION (Mon-Fri 8am-5pm)

Main:	(949) 333-1000	info@bcscsconsultants.com
Main Fax:	(949) 333-1001	info@bcscsconsultants.com
Customer Service:	(949) 333-1010	support@bcscsconsultants.com
IT Support:	(949) 333-1040	ITsupport@bcscsconsultants.com
Sales:	(949) 333-1020	sales@bcscsconsultants.com
Website	www.bcscsconsultants.com	

OTHER SERVICES

- **CARRIER SERVICES:** Data Center, Internet Access, Voice Services, & Wireless Services
- **HOSTED SOLUTIONS**
- **IT NETWORK SERVICES:** Anti-Spam, Backup Disaster Recovery, Computer Services, Managed Services, Server & Network Design, & Wireless Security
- **STRUCTURED CABLING:** Voice & Data Cabling
- **TELECOM:** Unified Communications, Voice & Video Conferencing, VOIP, Wireless Communications
- **VIDEO CONFERENCING & VIDEO SURVEILLANCE**

Maximize your communication system's performance, while protecting your investments, giving you peace of mind and service priority with BCS's **Customer For Life (CFL) Cisco Maintenance Program**. Call or email our Sales Team for pricing.

Everything Your Business Needs



